

ORACLE SOLARIS CLUSTER INTEROPERABILITY MATRIX

| EMC VNX Family – Unified Storage | |
|--|--|
| Storage Supported² (BLOCK) | VNX 5100, 5200, 5300, 5400, 5500, 5600, 5700, 5800, 7500, 7600, 8000, F5000, F7000 VNX e1600, 3100, 3150, 3200, 3300 Unity 300, 300F, 350F, 380, 380F, 400, 400F, 450F, 480, 480F, 500, 500F, 550F, 600, 600F, 650F, 680, 680F, 880, 880F |
| SPARC | |
| Oracle Servers¹ | Sun Enterprise: T2000 (sysfw 6.7.11 or later required), T5120, T5140, T5240, T5440 SPARC Enterprise: M3000, M4000, M5000, M8000, M9000 SPARC T-Series: T3-1, T3-1B, T3-2, T3-4, T4-1, T4-1B, T4-2, T4-4 Sun Netra: T5220, T5440, T3-1, T3-1BA, T4-1, T4-1B, T4-2 SPARC: T5-1B, T5-2, T5-4, T5-8, M5-32, M6-32, T7-1, T7-2, T7-4, M7-8, M7-16, S7-2, S7-2L, T8-1, T8-2, T8-4, M8-8 Fujitsu M10: M10-1, M10-4, M10-4S |
| Oracle Solaris Operating system | Oracle Solaris 11, 11.1, 11.2, 11.3, 11.4 ⁸ |
| Oracle Solaris Cluster Software^{4,5,6,7} | OSC 4.0, 4.1, 4.2, 4.3, 4.4 |
| Maximum Number Of Nodes | 6 |
| Multi-Path Driver Oracle Solaris | Oracle SAN driver bundled in OS for Oracle Solaris 11 releases |
| Multi-Path Driver EMC Option | EMC PowerPath 5.5 P06, 6.0-6.0 P02 |

| | |
|--|---|
| Host Adapters | <p>SG-XPCI1FC-EM2, SG-XPCI2FC-EM2, SG-XPCI1FC-EM4-Z, SG-XPCI2FC-EM4-Z SG-XPCI1FC-QL2, SG-XPCI1FC-QF2, SG-XPCI2FC-QF2, SG-XPCI2FC-QF2-Z, SG-XPCI1FC-QF4, SG-XPCI2FC-QF4</p> <p>SG-XPCIE1FC-EM4, SG-XPCIE2FC-EM4, SG-XPCIE1FC-QF4, SG-XPCIE2FC-QF4 SG-XPCIE2FC-EB4-Z, SG-XPCIE2FC-EB4-N, SG-XPCIE2FC-QB4-Z</p> <p>SG-XPCIE1FC-QF8-Z, SG-XPCIE1FC-EM8-Z, SG-XPCIE2FC-QF8-Z, SG-XPCIE2FC-EM8-Z SG-XPCIE1FC-QF8-N, SG-XPCI1EFC-EM8-N, SG-XPCIE2FC-QF8-N, SG-XPCIE2FC-EM8-N</p> <p>SG-XPCIEFCGBE-Q8-Z, SG-XPCIEFCGBE-Q8-N, SG-XPCIEFCGBE-E8-Z, SG-XPCIEFCGBE-E8-N 16 Gb HBAs⁸: 7101674, 7101682, 7101684, 7101690 "Native" HBAs supported³: Qlogic, Emulex</p> |
| SAN Switches | <p>Unless an exception is explicitly called out, any FC SAN switch can be used with Solaris Cluster. For supported switches, please refer to EMC's interoperability matrix at https://elabnavigator.emc.com/ You may also refer to http://www.oracle.com/us/products/servers-storage/storage/storage-networking/index.htm for Oracle supported switches.</p> |
| X86 (64 bit) | |
| Oracle Servers¹ X86 | <p>Sun Fire: x4170M2, x4270M2, x4470, x4470M2, x4800, x4800M2, X3-2, X3-2L, X4-2, X4-2L, X4-4, X4-8, X5-2, X5-2L, X5-4, X6-2, X6-2L Sun Blade: x6270M2, X4-2B Sun Netra: x4250, x6270M2, X3-2, X5-2</p> |
| Oracle Solaris Operating system | Oracle Solaris 11, 11.1, 11.2, 11.3, 11.4 |
| Oracle Solaris Cluster Software^{4,5,6,7} | OSC 4.0, 4.1, 4.2, 4.3, 4.4 |
| Maximum Number Of Nodes | 4 |
| Multi-Path Driver Oracle Solaris | Oracle SAN driver bundled in OS for Oracle Solaris 11 releases |
| Multi-Path Driver EMC Option | EMC PowerPath 5.5 P06, 6.0-6.0 P02 |

| | |
|--|---|
| Host Adapters | <p>SG-XPCIE1FC-EM8-Z, SG-XPCIE1FC-QF8-Z, SG-XPCIE1FC-EM8-N, SG-XPCIE1FC-QF8-N SG-XPCIE2FC-EM8-Z, SG-XPCIE2FC-QF8-Z, SG-XPCIE2FC-EM8-N, SG-XPCIE2FC-QF8-N</p> <p>SG-XPCI2FC-EM4, SG-XPCI2FC-EM4-Z, SG-XPCI2FC-QF4 SG-XPCIE2FC-EM4, SG-XPCIE2FC-QF4</p> <p>SG-XPCIEFCGBE-E8-Z, SG-XPCIEFCGBE-Q8-Z 16 Gb HBAs: 7101674, 7101682, 7101684, 7101690 "Native" HBAs supported³: Qlogic, Emulex</p> |
| SAN Switches | <p>Unless an exception is explicitly called out, any FC SAN switch can be used with Solaris Cluster. For supported switches, please refer to EMC's interoperability matrix at https://elabnavigator.emc.com/ You may also refer to http://www.oracle.com/us/products/servers-storage/storage/storage-networking/index.htm for Oracle supported switches.</p> |
| <p>1. Go to My Oracle Support (MOS) or http://myoraclesupport.com For minimum supported Oracle Solaris operating environment versions, HBAs, patches and other supported options for list servers. This matrix is intended to be a high level overview of support. It is not a configuration guide.</p> | |
| <p>2. Please refer to EMC's interoperability matrix at https://elabnavigator.emc.com/ for specific configurations, min microcode versions, Volume Manager support, notes and any restrictions.</p> | |
| <p>3. "Native" HBAs supported by Oracle Solaris: Non-Sun HBAs require that Sun drivers be utilized. See partner handbook for more info (a support account is required), if needed: https://support.oracle.com/handbook_partner/index.html</p> | |
| <p>4. QFS 5.3 supported.</p> | |
| <p>5. EMC supports ZFS in an Oracle Solaris Cluster environment.</p> | |
| <p>6. Before you use the create subcommand, ensure that the /etc/netmasks file has IP-address subnet and netmask entries for all logical hostnames. If necessary, edit the /etc/netmasks file to add any missing entries.</p> | |
| <p>7. 16 Gb HBAs are supported in specific OSC and Solaris releases with a very specific set of servers. Please consult MOS for details. Helpful link: http://www.oracle.com/technetwork/documentation/oracle-storage-networking-190061.html</p> | |
| <p>8. Some legacy SPARC servers do not support Oracle Solaris 11.4 See the following link for details. https://www.oracle.com/technetwork/systems/end-of-notices/eonsolaris11-392732.html#11.4</p> | |

Contact Us

For more information about Oracle Solaris Cluster, visit oracle.com or call +1.800.ORACLE1 to speak to an Oracle representative.

Copyright © 2019, Oracle and/or its affiliates. All rights reserved.

This document is provided for information purposes only and the contents hereof are subject to change without notice.

This document is not warranted to be error-free, nor subject to any other warranties or conditions, whether expressed orally or implied in law, including implied warranties and conditions of merchantability or fitness for a particular purpose. We specifically disclaim any liability with respect to this document and no contractual obligations are formed either directly or indirectly by this document. This document may not be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, without our prior written permission.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. UNIX is a registered trademark licensed through X/Open Company, Ltd. 0410



Oracle is committed to developing practices and products that help protect the environment